

Duration : 3 Hours

Marks : 80

- 1] Question no. 1 is Compulsory
- 2] Attempt any three questions out of remaining questions
- 3] Assume suitable data if require

Q1 Attempt any Four (20 Marks)

- a) Calculate charge density due to electric flux density  $\vec{D} = 4r \sin \theta \hat{a}_r + 2r \cos \theta \hat{a}_\theta + 2z^2 \hat{a}_z \text{ C/m}^2$
- b) Obtain point format of Continuity equation
- c) Express Biot Savart's law in vector format
- d) For parallel plates capacitor with plate area  $10\text{cm}^2$  and plates saperation  $3\text{mm}$  has voltage of  $100 \sin 10^3 t \text{ V}$  applied to its plates. Calculate displacement current density ( $\epsilon = 2\epsilon_0$ )
- e) Define following terms:
  - Uniform Plane waves
  - TEM wave
- f) Define the term Characteristic Impedance, Write expression for the same for Lossy and Lossless lines
- g) Show that  $\vec{E} = -\nabla V$

Q. 2

(20 Marks)

- a) A sheet charge of  $\rho_s = 2\text{nC/m}^2$  located at  $x = 2$  in free space and line charge  $\rho_l = 20\text{nC/m}$  is located at  $x = 1$  &  $z = 4$ , find electric field at the origin and direction of electric field at  $(4,5,6)$
- b) For infinite long conductor of radius 'a' carrying current I, determine Magnetic field everywhere.

Q. 3

(20 Marks)

- a) Explain in brief Maxwell's Equation for Time varying field in Integral and Point format, also give their significance
- b) Magnetic field component of an EM wave propagating through a non-magnetic medium ( $\mu = \mu_0$ ) is:

$$\vec{H} = 25 \sin(2 \times 10^8 t + 6x) \hat{a}_y \text{ mA/m}$$

Determine:

- The direction of wave propagation
- The permittivity
- Electric Field

Q. 4

(20 Marks)

List boundary conditions for time varying field if given that:

$$\vec{D} = 50\hat{a}_x + 80\hat{a}_y - 30\hat{a}_z \text{ nC/m}^2$$

In region  $x \geq 0$  where  $\epsilon = 2.1\epsilon_0$ . Find Electric charge density for region  $x \leq 0$  where  $\epsilon = 7.6\epsilon_0$ .

Obtain Poission's and Laplacian's Equation used to solve boundary problems for conducting plates described as  $V(z=0) = 0\text{V}$  and  $V(z=2\text{mm}) = 50\text{V}$ . Determine:

- V
- $\vec{E}$
- $\vec{D}$

Q. 5

- a) Lossless  $50\Omega$  transmission line terminated by a load impedance  $Z_L = 75 + 60j \Omega$ , using Smith chart determine:
- Reflection Coefficient
  - SWR
  - Input Impedance at  $0.2\lambda$  from load verifying the same using analytical solution.
- b) Obtain Integral form of Poynting Theorem and Explain significance of each term

(20 Mark)

Q. 6 Write short note on

- Electric Dipole
- Electrostatic discharge
- Magnetic Levitation
- Wave propagation through lossy dielectrics

(20 Mark)